

Driver overview

Fixture	min. Vf (V)	max. Vf (V)	max. current (mA)	CLS ND 001		CLS ND 004		CLS ND UNI		CLS MD 001		CLS MD 004		CLS VD 001		CLS VD 004		CLS VD 008		CLS DD 001		CLS DD UNI		CLS CD UNI		CLS LDC-41-G4			
				Supply (Vac)		100-240		198-264		198-264		198-264		198-240		99-264		99-264		99-264		99-264		99-264		99-264		48VDC	
				Dimmable		No		No		No		Mains		Mains		1-10V		1-10V		1-10V		DALI		DALI		CASAMBI		DMX	
				Current (mA)		700		250-1000		300-1050		700		350-750		350-900		350-900		250-700		250-700		350-700		350-700		250-1000	
				min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.	min.	max.
<i>Florence</i>	2,75	3,15	700	1	5	4	14	3	13	3	4	1	14	1	8	1	14	1	22	1	8	4	16	4	16	1	14		
<i>Focus Micro G2</i>	2,75	3,15	350	-	-	4	14	6	13	-	-	1	14	1	13	1	14	1	35	1	13	4	17	4	17	1	14		
<i>Focus Compact G3</i>	2,75	3,15	700	1	5	4	14	3	13	3	4	1	14	1	8	1	14	1	22	1	8	4	16	4	16	1	14		
<i>Focus HP</i>	5,5	6,5	700	1	2	2	6	2	6	2	2	1	7	1	4	1	7	1	10	1	4	2	7	2	7	1	6		
<i>Focus G4</i>	5,5	6,5	700	1	2	2	6	2	6	2	2	1	7	1	4	1	7	1	10	1	4	2	7	2	7	1	6		
<i>Luxo 3 CoB</i>	9	10,5	700	1	1	2	4	1	4	1	1	1	4	1	2	1	4	1	6	1	2	2	4	2	4	1	4		
<i>Ultima</i>	22	26	700	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Lina HP 30</i>	14	16	500	-	-	1	2	1	2	-	-	1	2	1	2	1	2	1	6	1	2	1	3	1	3	1	2		
<i>Lina HP 55</i>	29	31	500	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	3	1	1	1	1	1	1	1	1		
<i>Lina HP 80</i>	42	44	500	-	-	1	1	1	1	-	-	1	1	-	-	1	1	1	2	-	-	1	1	1	1	1	1		
<i>Lina HP 105*</i>	58	61	500	-	-	-	-	-	-	-	-	-	-	-	-	-	-	1	1	-	-	-	-	-	-	-	-		
<i>Lina HP 130*</i>	73	76	500	-	-	-	-	-	-	-	-	-	-	-	-	-	-	1	1	-	-	-	-	-	-	-	-		
<i>Lina DF 30</i>	11	13	500	-	-	1	3	1	3	-	-	1	3	1	3	1	3	1	7	1	3	1	3	1	4	1	3		
<i>Lina DF 55</i>	22	26	500	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	3	1	1	1	1	1	2	1	1		
<i>Lina DF 80</i>	33	39	500	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Lina DF 105*</i>	44	52	500	-	-	-	-	-	-	-	-	-	-	-	-	-	-	1	1	-	-	-	-	1	1	-	-		
<i>Mika</i>	34	36	700	-	-	1	1	1	1	-	-	1	1	-	-	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Emerald 4</i>	34	36	350	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Emerald 5</i>	34	36	500	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Emerald 6</i>	34	36	700	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		
<i>Emerald 7</i>	34	36	1000	-	-	1	1	1	1	-	-	1	1	1	1	1	1	1	2	1	1	1	1	1	1	1	1		

* These lengths of the Lina series are available on request.
 For more information please contact us via info@cls-led.com or by phone +31 26 326 36 76
 V1.0 2026